


- [File](#)
- [File history](#)
- [File usage](#)

Function	Control Command			Command example
	Command code	Parameter code	CR	
POWER ON/STANDBY change	PW	ON	<CR>	PWON<CR>
		STANDBY	<CR>	PWSTANDBY<CR>
Request Power Status		?	<CR>	PW?<CR>
MAIN-ZONE ON/OFF change	ZM	ON	<CR>	ZMON<CR>
		OFF	<CR>	ZMOFF<CR>
Request ZM Status		?	<CR>	ZM?<CR>
Favorite Station 1-4 Mode select	ZM	FAVORITE1	<CR>	ZMFAVORITE1<CR>
		FAVORITE2	<CR>	ZMFAVORITE2<CR>
		FAVORITE3	<CR>	ZMFAVORITE3<CR>
		FAVORITE4	<CR>	ZMFAVORITE4<CR>
Favorite Station 1-4 Mode memory		FAVORITE1 MEMORY	<CR>	ZMFAVORITE1 MEMO
		FAVORITE2 MEMORY	<CR>	ZMFAVORITE2 MEMO
		FAVORITE3 MEMORY	<CR>	ZMFAVORITE3 MEMO
		FAVORITE4 MEMORY	<CR>	ZMFAVORITE4 MEMO
MASTER VOLUME UP/DOWN , direct change to **dB	MV	UP	<CR>	MVUP<CR>
** 00 to 99 by ASCII , 80 = 0dB, 99 = —(MIN) , -80.5 = 99.5		DOWN	<CR>	MVDOWN<CR>
12model 80 = 0dB, 00 = —(MIN) , 005=-79.5dB, 98=+18dB		**	<CR>	MV80<CR>
Request MV Status		?	<CR>	MV?<CR>
CHANNEL VOLUME UP/DOWN , direct change to **dB	CV	FL UP	<CR>	CVFL UP<CR>
—FRONT Lch		FL DOWN	<CR>	CVFL DOWN<CR>
** 38 to 62 by ASCII , 50=0dB		FL **	<CR>	CVFL 50<CR>
		FR UP	<CR>	CVFR UP<CR>
—FRONT Rch		FR DOWN	<CR>	CVFR DOWN<CR>
** 38 to 62 by ASCII , 50=0dB		FR **	<CR>	CVFR 50<CR>
		C UP	<CR>	CVC UP<CR>

No higher resolution available.
[SDK_3.png](#) (775 × 518 pixels, file size: 132 KB, MIME type: image/png)

File history

Click on a date/time to view the file as it appeared at that time.

Date/Time	Thumbnail	Dimensions	User	Comment
current 11:58, 24 September 2012		775 × 518 (132 KB)	Fruxxx (Talk contribs)	

File usage

The following page links to this file:

- [IRidium DDK](#)